



# **DISIS 2016**

## Incremental Long-Term Congestion Rights Study Report

GEN-2016-153

Published on 08/06/2021

By SPP Generation Interconnections Dept.

## REVISION HISTORY

---

DATE OR VERSION NUMBER	AUTHOR	CHANGE DESCRIPTION	COMMENTS
05/06/2021	SPP	Initial report issued.	
08/06/2021	SPP	Update cost allocation resulting from Restudy	

# CONTENTS

---

- Revision History ..... i
- 1 Introduction ..... 1
- 2 Study Inputs ..... 2
  - Model Basis ..... 2
  - Monitored Facilities ..... 2
  - Contingency Events ..... 2
  - Sponsored Upgrades ..... 2
  - Contingent Upgrades ..... 3
  - Sponsor Transfer Paths ..... 3
- 3 Study Methodology ..... 4
  - Transfer Analysis ..... 4
- 4 ILTCR Study Results ..... 5
- 5 Conclusion ..... 6
- Appendix A ..... 1

# 1 INTRODUCTION

---

Incremental Long-Term Congestion Rights (ILTCRs) were made available by FERC 681 Guideline 3 as a reimbursement mechanism for sponsors of transmission upgrades. The guideline specifies that long-term firm transmission rights made feasible by transmission upgrades or expansions must be available upon request to any party that pays for such upgrades or expansions in accordance with the transmission organization's prevailing cost allocation methods for upgrades or expansions. Effective July 1, 2020, ILTCR is the default cost recovery mechanism for eligible Network Upgrades (NU) with Directly Assigned Upgrade Cost (DAUC) as a result of a Generation Interconnection Study (GIS), Aggregate Transmission Service Study (ATSS), or a Sponsored Upgrade Study in SPP.

The objective of the ILTCR analysis is to determine the incremental Available Transfer Capability (ATC) created on each of the Customer submitted source-to-sink paths over a ten-year period resulting from the construction of the Sponsored Upgrade. The Upgrade Sponsor may then have the option to use the results of this study to obtain candidate ILTCRs on the path selected.

The ILTCR study process was completed for GEN-2016-153 (the Customer) that has Directly Assigned Upgrade Costs (DAUC) for the following network upgrades from DISIS 2016-002 Studies.

- GEN-2016-119 Tap – Arcadia 345 kV
- Viola 345/138 kV Transformer Ckt2

## 2 STUDY INPUTS

---

### *MODEL BASIS*

The 2020 ITP Transmission Services (TS) cases were the starting point for the analysis. The following details specify the particular models utilized for this evaluation.

- Model years 2022, 2025, 2030
  - Summer Peak (2025SP, 2030SP)
  - Winter Peak (2022WP, 2025WP, 2030WP)
  - Light Load (2025LP, 2030LP)

### *MONITORED FACILITIES*

The monitored elements include all SPP control area branches, ties, and buses 69 kV and above, and all first tier Non-SPP control area branches and ties 100 kV and above. NERC Power Transfer Distribution Flowgates for SPP and first tier Non-SPP control areas are monitored. Additional NERC Flowgates are monitored in second tier or greater Non-SPP control areas.

- All branches and ties within the following areas:
  - SPP Internal Areas for 60kV – 999kV facilities:
    - 515 – 546, 640 – 659, 661, 998, 999
- NERC, SPP, and Tier 1 Permanent Monitor Flowgates (thermal)

### *CONTINGENCY EVENTS*

The contingency set includes all SPP control area branches and ties 69kV and above, first tier Non-SPP control area branches and ties 115 kV and above, any defined contingencies for these control areas, and generation unit outages for the SPP control areas with SPP reserve share program redispatch.

- All branches, ties, shunts, and generators within the following areas:
  - SPP Internal Areas for 60kV – 999kV facilities:
    - 515 – 546, 640, 641, 642, 645, 650, 652, 659, 998, 999
  - SPP External Areas for 100kV – 999kV facilities:
    - 327, 330, 351, 356, 502, 600, 615, 620, 627, 635, 661, 672, 680
- NERC, SPP, and Tier 1 Permanent Contingent Flowgates
- SPP T.O. Specific P1, P2, P4, and P5 TPL-004-1 Contingencies

### *SPONSORED UPGRADES*

For each Cluster Group with participating Customers, their Sponsored Upgrades were sorted based on construction lead-time in order to reflect the sequence of in-service dates for the upgrades. Each Sponsored Upgrade was evaluated sequentially and as a standalone addition. Sequentially, the first Sponsored Upgrade was evaluated in comparison to the TS Case. The second Sponsored Upgrade was evaluated on top of the previously added Sponsored Upgrade. The process was repeated until all Sponsored Upgrades were evaluated. Sponsored Upgrades that share the same construction lead-time were evaluated as incremental upgrades to the final set of Sponsored Upgrades with the

same lead-times. The studied Sponsored Upgrades and associated lead time for the Customer is listed in Table 2-1.

**Table 2-1: Sponsored Upgrades**

Group	Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
8	122792	Viola 345/138 kV Transformer Ckt2	24
8	122791	GEN-2016-119 Tap – Arcadia 345kV	36

### ***CONTINGENT UPGRADES***

Contingent upgrades are not yet in-service. These facilities have been assigned to higher queued interconnection customers. These facilities were included in the models respective of their estimated lead-time for this study prior to determining the incremental transfer amount that each Sponsored Upgrade provided. The list of contingent upgrades and their associated lead-time for the participating Customers is listed in Table 2-2.

**Table 2-2: Contingent Upgrade Sequence**

Group	Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
8	-	Clearwater – Viola 138kV CKT1	6
8	-	Gill – Viola 138kV CKT1	6
8	50582	Viola 345/138 kV Transformer CKT1	6
8	-	WolfCreek – Blackberry 345kV CKT1	72
9	-	NTC 200220 (R-Plan)	48

### ***SPONSOR TRANSFER PATHS***

The Customer is eligible to select up to three (3) source-to-sink transfer paths per Sponsored Upgrade. The list of valid source-to-sink paths are posted on the SPP OASIS site under Source/Sink Summary and were available to Customers with a valid OASIS certificate.

Customers may select paths for ILTCR studies using their new generator that was studied as a source. The generator must be registered in the Marketplace before it is able to participate in the Congestion Hedging process.

Each source-to-sink transfer path was collected by SPP for the Customer and those submissions are captured in the Results section.

## 3 STUDY METHODOLOGY

---

### *TRANSFER ANALYSIS*

A DC transfer analysis was conducted using PowerGEM TARA to determine the limiting flowgates in each applicable case for the respective transfer paths provided by the Customer. Constraints were defined as any overloaded facility in which the transfer had a three (3) percent or more TDF or OTDF impact for system intact or contingency conditions respectively. AC Contingency Analysis was performed on each case to identify existing overloaded flowgates that were not caused by the Customer, Sponsored Upgrade, or the source-to-sink transfer path. These flowgates were filtered out of the transfer analysis results for the respective case in which they were reported in the AC Contingency Analysis.

Once the initial DC limiting flowgates were filtered to valid results, the top five (5) limiting flowgates in each applicable case for the respective transfer paths provided by the Customer were AC verified. If the AC verified results reported a non-converged condition and all other AC verified transfers were not zero, then the AC non-converged condition was reviewed for appropriate adjustments until an AC transfer limit was established. If no adjustments were found to resolve the AC non-converged condition, then the AC transfer limit was reported as 0 MW to reflect the condition in which no transfer could be achieved.

With the transfer limits AC verified, the deltas between the minimum AC transfer amounts across all analyzed cases for each path with and without the associated Sponsored Upgrade were determined as follows:

- If  $ATC_{pre-NU} < 0$  and  $ATC_{post-NU} < 0$ , then individual increment = 0
- If  $ATC_{pre-NU} < 0$  and  $ATC_{post-NU} > 0$ , then individual increment =  $ATC_{post-NU}$
- If  $ATC_{pre-NU} > 0$  and  $ATC_{post-NU} > 0$ , then individual increment =  $ATC_{post-NU} - ATC_{pre-NU}$

If the Sponsored Upgrade costs were shared between multiple Customers, then the minimum delta was allocated to each participating Customer in the same proportion as the pro-rata share of the total cost of the upgrade allocated. The lowest amount of candidate MWs that can be awarded is 0.1 MW. Therefore, any candidate MWs below 0.1 MWs is reported as 0.0 MWs.

## 4 ILTCR STUDY RESULTS

Table 4-1 summarizes the minimum incremental ATC created across all seasons for each of the source-to-sink paths provided by the Customer for the Network Upgrades.

Appendix A includes the detail results of the top five (5) most limiting flowgates for each transfer path as submitted by the Customer.

**Table 4-1: GEN-2016-153 Candidate ILTCRs**

NU #	NU	Source	Sink	Min Delta (MW)	Cost Allocation (%)	cILTCR (MW)
122791	GEN-2016-119 Tap – Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	0	2.92%	0.0
122791	GEN-2016-119 Tap – Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	0	2.92%	0.0
122791	GEN-2016-119 Tap – Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	15.5	2.92%	0.4
122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPCO1	OKGE_OKGE	1.9	49.29%	0.9
122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPCO1	OPPD_OPPD	0	49.29%	0.0
122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPCO1	WR_WR	219.2	49.29%	108.0



## 5 CONCLUSION

---

The ILTCR analysis determined the incremental ATC created on the Customer submitted source-to-sink paths as provided by the associated Sponsored Upgrade. The Customer may choose the one source-to-sink path in which to receive candidate ILTCRs based on the ATC results presented. If a source-to-sink path that reported no incremental ATC (0 MW) is chosen, then the Customer will not receive any candidate ILTCRs for the Sponsored Upgrade. This data will be included in applicable agreement(s) and executed before filing with FERC.

The Customer must notify SPP 45 days in advance of energization of the associated Sponsored Upgrade via RMS ticket. Tracking of the Sponsored Upgrade progress can be achieved by utilizing the SPP Quarterly Project Tracking workbooks posted on the SPP website. Once the Sponsored Upgrade is energized, SPP will make available TCR MWs for the candidate ILTCR until the end of that TCR year in the next feasible monthly TCR auction.

# APENDIX A

Group	IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	1	2025SP	528334 LE-NRTH_INT3 115 528618 LE-LOVINTON2 69.0 1	5533	11.3	11.3	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	2	2030LP	524267 BUSHLAND 6 230 524623 DEAFSMITH 6 230 1	90959	35.9	38.5	2.6
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	3	2030LP	526524 WOLFFORTH 3 115 526736 TERRY_CNTY 3 115 1	105461	390.6	257.6	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	4	2030LP	514714 WOODRNG4 138 1	81306	411	401	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WFEC_WFEC	5	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	416.8	422.8	6
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	1	2030SP	645458 S3458 3 345 645456 S3456 3 345 1	5138	38.5	38.1	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	2	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	606.9	621.7	14.8
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	3	2025LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	613.9	643.7	29.8
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	4	2030SP	532798 VIOLA 7 345 997753 VIOLA TX-1 138 1	8311	1200.6	1154.6	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	OPPD_OPPD	5	2030SP	997753 VIOLA TX-1 138 533075 VIOLA 4 138 1	8311	1220.6	1162.2	0
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	1	2030LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	650.8	666.3	15.5
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	2	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	659.8	689.5	29.7
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	3	2025LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	673.7	690.2	16.5
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	4	2025LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	680.2	712.1	31.9
G08	GEN-2016-153	122791	GEN-2016-119 Tap - Arcadia 345 kV	WR_FLATRIDGE2TSA	WR_WR	5	2030SP	532798 VIOLA 7 345 997753 VIOLA TX-1 138 1	8311	1086.8	1086.5	0

Group	IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OKGE_OKGE	1	2030SP	998135 CIMARON1 138 514898 CIMARON4 138 1	91056	102.7	104.6	1.9
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OKGE_OKGE	2	2025SP	998135 CIMARON1 138 514898 CIMARON4 138 1	91056	126.7	128.8	2.1
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OKGE_OKGE	3	2030LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	330	362.6	32.6
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OKGE_OKGE	4	2025LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	341.3	370.6	29.3
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OKGE_OKGE	5	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	343.8	377.3	33.5
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OPPD_OPPD	1	2030SP	645458 S3458 3 345 645456 S3456 3 345 1	5138	38.7	38.5	0
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OPPD_OPPD	2	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	473	606.9	133.9
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OPPD_OPPD	3	2025LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	481.2	613.9	132.7
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OPPD_OPPD	4	2030SP	997753 VIOLA TX-1 138 533075 VIOLA 4 138 1	8311	482.9	1200.6	717.7
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	OPPD_OPPD	5	2030SP	532798 VIOLA 7 345 997753 VIOLA TX-1 138 1	8311	490.5	1220.6	730.1
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	WR_WR	1	2030LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	431.6	650.8	219.2
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	WR_WR	2	2025LP	998158 WOODRNG2 138 514714 WOODRNG4 138 1	81306	434.1	659.8	225.7
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	WR_WR	3	2030LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	437.4	673.7	236.3
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	WR_WR	4	2025LP	514715 WOODRNG7 345 998158 WOODRNG2 138 1	81306	437.9	680.2	242.3
G08	GEN-2016-153	122792	Viola 345/138 kV Transformer Ckt2	WR_FLATRIDGE2SWPC01	WR_WR	5	2030SP	532798 VIOLA 7 345 997753 VIOLA TX-1 138 1	8311	444.2	1086.8	642.6