



DISIS 2017-002

Incremental Long-Term Congestion Rights Study Report

GEN-2017-184

Published on 10/31/2024

By SPP Generation Interconnections Dept.

REVISION HISTORY

DATE OR VERSION NUMBER	AUTHOR	CHANGE DESCRIPTION
08/21/2024	SPP	Initial Report
09/23/2024	SPP	Updated Sponsored Upgrades to Network Upgrades, Updated Sponsor to Customer
10/31/2024	SPP	Updated results with invalid contingency events removed, Updated Candidate ILTCR(s)

CONTENTS

Revision History i

Introduction 1

Study Inputs 2

 Model Basis 2

 Monitored Facilities 2

 Contingency Events 2

 Network Upgrades 2

 Contingent Upgrades 3

 Customer Transfer Paths 3

Study Methodology 4

 Transfer Analysis 4

ILTCR Study Results 5

Conclusion 6

Appendix A 1

INTRODUCTION

Incremental Long-Term Congestion Rights (ILTCRs) were made available by FERC 685 Guideline 3 as a reimbursement mechanism for sponsors of transmission upgrades. The guideline specifies that long-term firm transmission rights made feasible by transmission upgrades or expansions must be available upon request to any party that pays for such upgrades or expansions in accordance with the transmission organization's prevailing cost allocation methods for upgrades or expansions. Effective July 1, 2020, ILTCR is the default cost recovery mechanism for eligible Network Upgrades (NU) with Directly Assigned Upgrade Cost (DAUC) as a result of a Generation Interconnection Study (GIS), Aggregate Transmission Service Study (ATSS), or a Sponsored Upgrade Study in SPP.

The objective of the ILTCR analysis is to determine the incremental Available Transfer Capability (ATC) created on each of the Upgrade Sponsor submitted source-to-sink paths over a ten-year period resulting from the construction of the Network Upgrade. The Upgrade Sponsor may then have the option to use the results of this study to obtain candidate ILTCRs on the path selected.

The ILTCR study process was completed for GEN-2017-184 (the Customer) that has Directly Assigned Upgrade Costs (DAUC) for the following network upgrades from DISIS 2017-002 Studies.

- Install a second 650 MVA TX at Nashua
- Terminal upgrades on the Roanridge to Nashua 161 kV line 1

STUDY INPUTS

MODEL BASIS

The 2023 ITP Transmission Services (TS) cases were the starting point for the analysis. The following details specify the particular models utilized for this evaluation.

- Model years 2026, 2027, 2028, 2033
 - Summer Peak (2026SP, 2027SP, 2028SP, 2033SP)
 - Winter Peak (2026WP, 2027WP, 2028WP, 2033WP)
 - Light Load (2027LP, 2028LP, 2033LP)

MONITORED FACILITIES

The monitored elements include all SPP control area branches, ties, and buses 69 kV and above, and all first tier Non-SPP control area branches and ties 100 kV and above. NERC Power Transfer Distribution Flowgates for SPP and first tier Non-SPP control areas are monitored. Additional NERC Flowgates are monitored in second tier or greater Non-SPP control areas.

- All branches and ties within the following areas:
 - SPP Internal Areas for 60kV – 999kV facilities:
 - 506– 546, 640 – 659, 998, 999
 - SPP External Areas for 100kV – 999kV facilities:
 - 327, 330, 351, 356, 502, 600, 615, 620, 627, 635, 661, 680
- NERC, SPP, and Tier 1 Permanent Monitor Flowgates (thermal)

CONTINGENCY EVENTS

The contingency set includes all SPP control area branches and ties 69kV and above, first tier Non-SPP control area branches and ties 115 kV and above, any defined contingencies for these control areas, and generation unit outages for the SPP control areas with SPP reserve share program redispatch.

- All branches, ties, shunts, and generators within the following areas:
 - SPP Internal Areas for 60kV – 999kV facilities:
 - 515 – 546, 640, 641, 642, 645, 650, 652, 659, 998, 999
 - SPP External Areas for 100kV – 999kV facilities:
 - 327, 330, 351, 356, 502, 600, 615, 620, 627, 635, 661, 680
- NERC, SPP, and Tier 1 Permanent Contingent Flowgates
- SPP T.O. Specific P1, P2, P4, and P5 TPL-004-1 Contingencies
- SPP T.O. Specific Op Guide Implementation

NETWORK UPGRADES

The Sponsored Upgrades were sorted based on construction lead-time in order to reflect the sequence of in-service dates for the upgrades. Each Network Upgrade was evaluated sequentially and as a standalone addition. Sequentially, the first Network Upgrade was evaluated in comparison to the TS Case. The second Network Upgrade was evaluated on top of the previously added Network Upgrade. The process was repeated until all Network Upgrades were evaluated. Network

Upgrades that share the same construction lead-time were evaluated as incremental upgrades to the final set of Network Upgrades with the same lead-times. The studied Network Upgrades and associated lead time for the Customer is listed in Table 0-1.

Table 0-1: Network Upgrades

Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
159068	Install a second 650 MVA TX at Nashua	48
159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	24

CONTINGENT UPGRADES

Contingent upgrades are not yet in-service. These facilities have been assigned to higher queued interconnection customers. These facilities were included in the models respective of their estimated lead-time for this study prior to determining the incremental transfer amount that each Network Upgrade provided. The list of contingent upgrades and their associated lead-time for the participating Customers is listed in Table 0-2.

Table 0-2: Contingent Upgrade Sequence

Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
NTC 210592/210626	Line - Wolf Creek - Blackberry 345 kV	6
NTC 210616	Multi - Minco - Pleasant Valley - Draper 345 kV	6
NTC 210627	Multi - Border - Woodward 345 kV Tap	12
NTC 210483	Multi - Park Community - Sunshine 138 kV	24
NTC 220738/TBD	Matthewson - Redbud 345 kV New Line	48
NTC 210618/200220	Multi - Gentleman - Cherry Co. - Holt Co. 345 kV	48

CUSTOMER TRANSFER PATHS

The Customer is eligible to select up to three (3) source-to-sink transfer paths per Network Upgrade. The list of valid source-to-sink paths is posted on the SPP OASIS site under Source/Sink Summary and were available to Customers with a valid OASIS certificate.

Customers may select paths for ILTCR studies using their new generator that was studied as a source. The generator must be registered in the Marketplace before it is able to participate in the Congestion Hedging process.

Each source-to-sink transfer path was collected by SPP for the Customer and those submissions are captured in the Results section.

STUDY METHODOLOGY

TRANSFER ANALYSIS

A DC transfer analysis was conducted using PowerGEM TARA to determine the limiting flowgates in each applicable case for the respective transfer paths provided by the Customer. Constraints were defined as any overloaded facility in which the transfer had a three (3) percent or more TDF or OTDF impact for system intact or contingency conditions respectively. AC Contingency Analysis was performed on each case to identify existing overloaded flowgates that were not caused by the Customer, Network Upgrade, or the source-to-sink transfer path. These flowgates were filtered out of the transfer analysis results for the respective case in which they were reported in the AC Contingency Analysis.

Once the initial DC limiting flowgates were filtered to valid results, the top five (5) limiting flowgates in each applicable case for the respective transfer paths provided by the Customer were AC verified. If the AC verified results reported a non-converged condition and all other AC verified transfers were not zero, then the AC non-converged condition was reviewed for appropriate adjustments until an AC transfer limit was established. If no adjustments were found to resolve the AC non-converged condition, then the AC transfer limit was reported as 0 MW to reflect the condition in which no transfer could be achieved.

With the transfer limits AC verified, the deltas between the minimum AC transfer amounts across all analyzed cases for each path with and without the associated Network Upgrade were determined as follows:

- If $ATC_{pre-NU} < 0$ and $ATC_{post-NU} < 0$, then individual increment = 0
- If $ATC_{pre-NU} < 0$ and $ATC_{post-NU} > 0$, then individual increment = $ATC_{post-NU}$
- If $ATC_{pre-NU} > 0$ and $ATC_{post-NU} > 0$, then individual increment = $ATC_{post-NU} - ATC_{pre-NU}$

If the Network Upgrade costs were shared between multiple Customers, then the minimum delta was allocated to each participating Customer in the same proportion as the pro-rata share of the total cost of the upgrade allocated. The lowest amount of candidate MWs that can be awarded is 0.1 MW. Therefore, any candidate MWs below 0.1 MWs is reported as 0.0 MWs.

ILTCR STUDY RESULTS

Table 0-1 summarizes the minimum incremental ATC created across all seasons for each of the source-to-sink paths provided by the Customer for the Network Upgrades.

Appendix A includes the detailed results of the top five (5) most limiting flowgates for each transfer path as submitted by the Customer.

Table 0-1: GEN-2017-184 Candidate ILTCRs

NU #	NU	Source	Sink	Min Delta (MW)	Cost Allocation (%)	cILTCR (MW)
159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	0	50.72%	0
159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	0	50.72%	0
159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	0	50.72%	0
159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	0	51.16%	0
159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	0	51.16%	0
159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	0	51.16%	0

CONCLUSION

The ILTCR analysis determined the incremental ATC created on the Customer submitted source-to-sink paths as provided by the associated Network Upgrade. The Customer may choose the one source-to-sink path in which to receive candidate ILTCRs based on the ATC results presented. If a source-to-sink path that reported no incremental ATC (0 MW) is chosen, then the Customer will not receive any candidate ILTCRs for the Network Upgrade. This data will be included in applicable agreement(s) and executed before filing with FERC.

The Customer must notify SPP 45 days in advance of energization of the associated Network Upgrade via RMS ticket. Tracking of the Network Upgrade progress can be achieved by utilizing the SPP Quarterly Project Tracking workbooks posted on the SPP website. Once the Network Upgrade is energized, SPP will make available TCR MWs for the candidate ILTCR until the end of that TCR year in the next feasible monthly TCR auction.

APPENDIX A

IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	1	33SP0	543666 NEASTN5 161 542987 GRAND 5 161 1	229577	812.1	711.7	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	2	33SP0	542987 GRAND 5 161 542989 NAVY 5 161 1	229577	812.4	712.5	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	3	28WP0	761383 G17-183-TAP 345 542980 NASHUA 7 345 1	229762	961.2	835.4	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	4	33SP0	542988 GRAND W5 161 542990 CROSTWN5 161 1	229569	976.2	897	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	KCPLHUB	5	28LP0	761383 G17-183-TAP 345 542980 NASHUA 7 345 1	229734	977.2	1073.6	96.4
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	1	33SP0	543666 NEASTN5 161 542987 GRAND 5 161 1	229577	812.1	711.7	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	2	33SP0	542987 GRAND 5 161 542989 NAVY 5 161 1	229577	812.4	712.5	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	3	28WP0	761383 G17-183-TAP 345 542980 NASHUA 7 345 1	229762	961.2	835.4	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	4	33SP0	542988 GRAND W5 161 542990 CROSTWN5 161 1	229569	976.2	897	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	MPS	5	28LP0	761383 G17-183-TAP 345 542980 NASHUA 7 345 1	229734	977.2	1073.6	96.4
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	1	28SP0	533696 LABETTS2 69.0 533672 ALTAMNS2 69.0 1	243089	271.5	271.5	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	2	33SP0	533696 LABETTS2 69.0 533672 ALTAMNS2 69.0 1	243089	310.3	310.3	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	3	28SP0	533211 ARNOLD 3 115 533218 PARALEL3 115 1	242774	316.6	316.4	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	4	33SP0	533211 ARNOLD 3 115 533218 PARALEL3 115 1	242774	320.5	320.3	0
GEN-2017-184	159068	Install a second 650 MVA TX at Nashua	GEN-2017-184 POI	WR_KMEA	5	33SP0	533332 KNOB HL3 115 533303 MARSHAL3 115 1	242837	466.4	466.3	0

Southwest Power Pool, Inc.

IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	1	33SP0	543666 NEASTN5 161 542987 GRAND 5 161 1	229577	812.1	812.1	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	2	33SP0	542987 GRAND 5 161 542989 NAVY 5 161 1	229577	812.4	812.4	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	3	33LP0	996874 NASHUA11 161 543028 NASHUA-5 161 11	229761	961.2	961.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	4	33LP0	542980 NASHUA 7 345 996874 NASHUA11 161 11	229761	976.2	976.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	KCPLHUB	5	28LP0	542980 NASHUA 7 345 996874 NASHUA11 161 11	229761	977.2	977.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	1	33SP0	543666 NEASTN5 161 542987 GRAND 5 161 1	229577	812.1	812.1	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	2	33SP0	542987 GRAND 5 161 542989 NAVY 5 161 1	229577	812.4	812.4	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	3	33LP0	996874 NASHUA11 161 543028 NASHUA-5 161 11	229761	961.2	961.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	4	33LP0	542980 NASHUA 7 345 996874 NASHUA11 161 11	229761	976.2	976.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	MPS	5	28LP0	542980 NASHUA 7 345 996874 NASHUA11 161 11	229761	977.2	977.2	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	1	26SP0	533696 LABETTS2 69.0 533672 ALTAMNS2 69.0 1	243089	222.9	222.9	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	2	28SP0	533696 LABETTS2 69.0 533672 ALTAMNS2 69.0 1	243089	271.5	271.5	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	3	28SP0	533211 ARNOLD 3 115 533218 PARALEL3 115 1	242774	316.6	316.6	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	4	33SP0	533211 ARNOLD 3 115 533218 PARALEL3 115 1	242774	320.5	320.5	0
GEN-2017-184	159069	Terminal upgrades on the Roanridge to Nashua 161 kV line 1	GEN-2017-184 POI	WR_KMEA	5	26SP0	533211 ARNOLD 3 115 533218 PARALEL3 115 1	242774	354.3	354.3	0