



DISIS 2017-001

Incremental Long-Term Congestion Rights
Study Report

GEN-2017-048

Published on 09/23/2022

By SPP Generation Interconnections Dept.

REVISION HISTORY

DATE OR VERSION NUMBER	AUTHOR	CHANGE DESCRIPTION	COMMENTS
09/01/2022	SPP	Initial report issued.	
09/23/2022	SPP	Updated report issued	

CONTENTS

Revision History.....	i
1 Introduction.....	1
2 Study Inputs.....	2
Model Basis	2
Monitored Facilities.....	2
Contingency Events.....	2
Sponsored Upgrades	2
Contingent Upgrades.....	3
Sponsor Transfer Paths.....	3
3 Study Methodology	4
Transfer Analysis	4
4 ILTCR Study Results	5
5 Conclusion	6
Appendix A.....	1

1 INTRODUCTION

Incremental Long-Term Congestion Rights (ILTCRs) were made available by FERC 685 Guideline 3 as a reimbursement mechanism for sponsors of transmission upgrades. The guideline specifies that long-term firm transmission rights made feasible by transmission upgrades or expansions must be available upon request to any party that pays for such upgrades or expansions in accordance with the transmission organization's prevailing cost allocation methods for upgrades or expansions. Effective July 1, 2020, ILTCR is the default cost recovery mechanism for eligible Network Upgrades (NU) with Directly Assigned Upgrade Cost (DAUC) as a result of a Generation Interconnection Study (GIS), Aggregate Transmission Service Study (ATSS), or a Sponsored Upgrade Study in SPP.

The objective of the ILTCR analysis is to determine the incremental Available Transfer Capability (ATC) created on each of the Customer submitted source-to-sink paths over a ten-year period resulting from the construction of the Sponsored Upgrade. The Upgrade Sponsor may then have the option to use the results of this study to obtain candidate ILTCRs on the path selected.

The ILTCR study process was completed for GEN-2017-048 (the Customer) that has Directly Assigned Upgrade Costs (DAUC) for the following network upgrades from DISIS 2017-001 Studies.

- Broadland 345/230kV Transformer Replacement (DISIS-2017-001)
- Neson to Tioga 230kV Rebuild (DISIS-2017-001)
- Jamestown 230kV Capacitive Reactive Support (DISIS-2017-001)

2 STUDY INPUTS

MODEL BASIS

The 2021 ITP Transmission Services (TS) cases were the starting point for the analysis. The following details specify the particular models utilized for this evaluation.

- Model years 2023, 2024, 2027, 2032
 - Summer Peak (2023SP, 2024SP, 2027SP, 2032SP)
 - Winter Peak (2023WP, 2024WP, 2027WP, 2032WP)
 - Light Load (2023LP, 2024LP, 2027LP, 2032LP)

MONITORED FACILITIES

The monitored elements include all SPP control area branches, ties, and buses 69 kV and above, and all first tier Non-SPP control area branches and ties 100 kV and above. NERC Power Transfer Distribution Flowgates for SPP and first tier Non-SPP control areas are monitored. Additional NERC Flowgates are monitored in second tier or greater Non-SPP control areas.

- All branches and ties within the following areas:
 - SPP Internal Areas for 60kV – 999kV facilities:
 - 506 – 546, 640 – 659, 998, 999
 - SPP External Areas for 100kV – 999kV facilities:
 - 327, 330, 351, 356, 502, 600, 615, 620, 627, 635, 661, 680
- NERC, SPP, and Tier 1 Permanent Monitor Flowgates (thermal)

CONTINGENCY EVENTS

The contingency set includes all SPP control area branches and ties 69kV and above, first tier Non-SPP control area branches and ties 115 kV and above, any defined contingencies for these control areas, and generation unit outages for the SPP control areas with SPP reserve share program redispatch.

- All branches, ties, shunts, and generators within the following areas:
 - SPP Internal Areas for 60kV – 999kV facilities:
 - 515 – 546, 640, 641, 642, 645, 650, 652, 659, 998, 999
 - SPP External Areas for 100kV – 999kV facilities:
 - 327, 330, 351, 356, 502, 600, 615, 620, 627, 635, 661, 680
- NERC, SPP, and Tier 1 Permanent Contingent Flowgates
- SPP T.O. Specific P1, P2, P4, and P5 TPL-004-1 Contingencies
- SPP T.O. Specific Op Guide Implementation

SPONSORED UPGRADES

The Sponsored Upgrades were sorted based on construction lead-time in order to reflect the sequence of in-service dates for the upgrades. Each Sponsored Upgrade was evaluated sequentially and as a standalone addition. Sequentially, the first Sponsored Upgrade was evaluated in comparison to the TS Case. The second Sponsored Upgrade was evaluated on top of the previously added Sponsored Upgrade. The process was repeated until all Sponsored Upgrades were evaluated.

Sponsored Upgrades that share the same construction lead-time were evaluated as incremental upgrades to the final set of Sponsored Upgrades with the same lead-times. The studied Sponsored Upgrades and associated lead time for the Customer is listed in Table 2-1.

Table 2-1: Sponsored Upgrades

Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	18
156269	Jamestown 230kV Capacitive Reactive Support (DISIS-2017-001)	30
143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	36

CONTINGENT UPGRADES

Contingent upgrades are not yet in-service. These facilities have been assigned to higher queued interconnection customers. These facilities were included in the models respective of their estimated lead-time for this study prior to determining the incremental transfer amount that each Sponsored Upgrade provided. The list of contingent upgrades and their associated lead-time for the participating Customers is listed in Table 2-2.

Table 2-2: Contingent Upgrade Sequence

Upgrade ID	Upgrade Name	Estimated Lead-Time (months)
82127	GEN-2015-093 Circuit Breaker Addition to Gracemont 138kV substation	0
NTC 210560	Neset - Northshore 230 kV Ckt 1 NTC 210560	15
NTC 2010609	Border 345kV Reactive Support NTC 210609	18
NTC 2010575/210587	Multi - Border - Woodward 345 kV Tap NTC 210575/210587	20
122598	Wolf Creek to Blackberry 345kV	60

SPONSOR TRANSFER PATHS

The Customer is eligible to select up to three (3) source-to-sink transfer paths per Sponsored Upgrade. The list of valid source-to-sink paths are posted on the SPP OASIS site under Source/Sink Summary and were available to Customers with a valid OASIS certificate.

Customers may select paths for ILTCR studies using their new generator that was studied as a source. The generator must be registered in the Marketplace before it is able to participate in the Congestion Hedging process.

Each source-to-sink transfer path was collected by SPP for the Customer and those submissions are captured in the Results section.

3 STUDY METHODOLOGY

TRANSFER ANALYSIS

A DC transfer analysis was conducted using PowerGEM TARA to determine the limiting flowgates in each applicable case for the respective transfer paths provided by the Customer. Constraints were defined as any overloaded facility in which the transfer had a three (3) percent or more TDF or OTDF impact for system intact or contingency conditions respectively. AC Contingency Analysis was performed on each case to identify existing overloaded flowgates that were not caused by the Customer, Sponsored Upgrade, or the source-to-sink transfer path. These flowgates were filtered out of the transfer analysis results for the respective case in which they were reported in the AC Contingency Analysis.

Once the initial DC limiting flowgates were filtered to valid results, the top five (5) limiting flowgates in each applicable case for the respective transfer paths provided by the Customer were AC verified. If the AC verified results reported a non-converged condition and all other AC verified transfers were not zero, then the AC non-converged condition was reviewed for appropriate adjustments until an AC transfer limit was established. If no adjustments were found to resolve the AC non-converged condition, then the AC transfer limit was reported as 0 MW to reflect the condition in which no transfer could be achieved.

With the transfer limits AC verified, the deltas between the minimum AC transfer amounts across all analyzed cases for each path with and without the associated Sponsored Upgrade were determined as follows:

- If ATC pre-NU < 0 and ATC post-NU < 0, then individual increment = 0
- If ATC pre-NU < 0 and ATC post-NU > 0, then individual increment = ATC post-NU
- If ATC pre-NU > 0 and ATC post-NU > 0, then individual increment = ATC post-NU – ATC pre-NU

If the Sponsored Upgrade costs were shared between multiple Customers, then the minimum delta was allocated to each participating Customer in the same proportion as the pro-rata share of the total cost of the upgrade allocated. The lowest amount of candidate MWs that can be awarded is 0.1 MW. Therefore, any candidate MWs below 0.1 MWs is reported as 0.0 MWs.

4 ILTCR STUDY RESULTS

Table 4-1 summarizes the minimum incremental ATC created across all seasons for each of the source-to-sink paths provided by the Customer for the Network Upgrades.

Appendix A includes the detailed results of the top five (5) most limiting flowgates for each transfer path as submitted by the Customer.

Table 4-1: GEN-2017-048 Candidate ILTCRs

NU #	NU	Source	Sink	Min Delta (MW)	Cost Allocation (%)	cILTCR (MW)
143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	0	65.41%	0
143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	0	65.41%	0
143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	0	65.41%	0
143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	0	100.00%	0
143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	0	100.00%	0
143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	0	100.00%	0
156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	0	66.22%	0
156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	0	66.22%	0
156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA.NE WHAMPTON	0	66.22%	0

5 CONCLUSION

The ILTCR analysis determined the incremental ATC created on the Customer submitted source-to-sink paths as provided by the associated Sponsored Upgrade. The Customer may choose the one source-to-sink path in which to receive candidate ILTCRs based on the ATC results presented. If a source-to-sink path that reported no incremental ATC (0 MW) is chosen, then the Customer will not receive any candidate ILTCRs for the Sponsored Upgrade. This data will be included in applicable agreement(s) and executed before filing with FERC.

The Customer must notify SPP 45 days in advance of energization of the associated Sponsored Upgrade via RMS ticket. Tracking of the Sponsored Upgrade progress can be achieved by utilizing the SPP Quarterly Project Tracking workbooks posted on the SPP website. Once the Sponsored Upgrade is energized, SPP will make available TCR MWs for the candidate ILTCR until the end of that TCR year in the next feasible monthly TCR auction.

APPENDIX A

IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	1	32SP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	182.4	182.4	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	2	32LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	585.7	585.7	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	3	27LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	613.5	613.5	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	4	24WP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P21:345:OTP:AUTO-SINGLE:BUFFALO3:JAMESTN3:1	619.3	619.3	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.AVS1	DPC	5	27WP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P21:345:OTP:AUTO-SINGLE:BUFFALO3:JAMESTN3:1	871.5	871.5	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	1	32SP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	153.4	153.4	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	2	27LP0	659139 NESET__-BE7 115 661085 TIOGA4 7 115 1	Base Case	304.4	304.4	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	3	27LP0	659139 NESET__-BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA_N_-MW7 115 655953 W.BANK_T-MW7 115 1	311.5	311.5	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	4	32LP0	659139 NESET__-BE7 115 661085 TIOGA4 7 115 1	Base Case	324.4	324.4	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.BEPM.LINDAHL	NSP	5	32LP0	659139 NESET__-BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA_N_-MW7 115 655953 W.BANK_T-MW7 115 1	328.5	328.5	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	1	32SP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	121.3	121.3	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	2	32LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	380.2	380.2	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	3	24WP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P21:345:OTP:AUTO-SINGLE:BUFFALO3:JAMESTN3:1	401.7	401.7	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	4	27SP0	652441 GARRISN4 230 659106 LELAND_O-BE4 230 1	652426 BISMARCK4 230 652466 HILKEN 4 230 1	435.1	435.1	0
GEN-2017-048	143226	Broadland 345/230kV Transformer Replacement (DISIS-2017-001)	WAUE.GARRISON.1_3	GRE	5	27LP0	652441 GARRISN4 230 659106 LELAND_O-BE4 230 1	652426 BISMARCK4 230 652466 HILKEN 4 230 1	439.1	439.1	0

Southwest Power Pool, Inc.

IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	1	23LP0	652501 ARMOUR 7 115 652510 FTRANDL7 115 1	652518 MTVERN 7 115 659123 STORLA_-BE7 115 1	88.1	88.1	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	2	24LP0	652501 ARMOUR 7 115 652510 FTRANDL7 115 1	652518 MTVERN 7 115 659123 STORLA_-BE7 115 1	88.4	88.4	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	3	27LP0	652501 ARMOUR 7 115 652510 FTRANDL7 115 1	652518 MTVERN 7 115 659123 STORLA_-BE7 115 1	88.9	88.9	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	4	32LP0	652501 ARMOUR 7 115 652510 FTRANDL7 115 1	652518 MTVERN 7 115 659123 STORLA_-BE7 115 1	89.8	89.8	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.AWD1.AURAWIND	WAUE OTP	5	23LP0	652518 MTVERN 7 115 652501 ARMOUR 7 115 1	652518 MTVERN 7 115 659123 STORLA_-BE7 115 1	98.6	98.6	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	1	32SP0	652427 BISMARCK7 115 661029 ESTBMRK7 115 1	P21:115:MDU::HESKETT:COLLINS:1:::	213.5	213.5	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	2	24SP0	652427 BISMARCK7 115 661029 ESTBMRK7 115 1	P21:115:MDU::HESKETT:COLLINS:1:::	262.2	262.2	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	3	27SP0	652427 BISMARCK7 115 661029 ESTBMRK7 115 1	P21:115:MDU::HESKETT:COLLINS:1:::	264.2	264.2	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	4	23SP0	652427 BISMARCK7 115 661029 ESTBMRK7 115 1	P21:115:MDU::HESKETT:COLLINS:1:::	273.9	273.9	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.LINDAHL	MDU	5	23LP0	659139 NESET_-BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA.N_-MW7 115 655953 W.BANK_T-MW7 115 1	290.8	290.8	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	1	27SP0	655924 STATELIN- MW7 115 655940 MONT -MW7 115 1	655924 STATELIN-MW7 115 655925 JUDSON -MW7 115 1	18.6	18.6	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	2	32SP0	655924 STATELIN- MW7 115 655940 MONT -MW7 115 1	655924 STATELIN-MW7 115 655925 JUDSON -MW7 115 1	24.4	24.4	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	3	27SP0	655924 STATELIN- MW7 115 655925 JUDSON -MW7 115 1	P21:115:UMZB:# 2540 #: SLN IN ND. OPENING OF LINE SECTION WITHOUT FAULT SLN-MNU:HV:	41.9	41.9	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	4	27SP0	655925 JUDSON -MW7 115 652421 WILISTN7 115 1	P21:115:UMZB:# 2540 #: SLN IN ND. OPENING OF LINE SECTION WITHOUT FAULT SLN-MNU:HV:	45.8	45.8	0
GEN-2017-048	143236	Neset to Tioga 230kV Rebuild (DISIS-2017-001)	WAUE.BEPM.PGS1	OTP	5	32SP0	655924 STATELIN- MW7 115 655925 JUDSON -MW7 115 1	P21:115:UMZB:# 2540 #: SLN IN ND. OPENING OF LINE SECTION WITHOUT FAULT SLN-MNU:HV:	46.2	46.2	0

Southwest Power Pool, Inc.

IC	NU	Network Upgrade Name	Source	Sink	Limit	Case	Monitored Facility	Contingency Name	Base FCITC	Upgrade FCITC	ATC Increase
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	1	32SP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	150.8	150.8	0
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	2	24WP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P21:345:OTP:AUTO-SINGLE:BUFFALO3:JAMESTN3:1	447	485	38
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	3	32LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	496.8	498.9	2.1
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	4	27LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	523.3	523.5	0.2
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.AVS1	GRE	5	24LP0	652435 FARGO 4 230 602006 SHEYNNE4 230 1	P12:345:MPC:JAMESTOWN-BISON:JAMESTN3:BISON 3	592.3	593.1	0.8
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	1	27LP0	659139 NESET__BE7 115 661085 TIOGA4 7 115 1	Base Case	304.4	304.4	0
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	2	24LP0	659139 NESET__BE7 115 661085 TIOGA4 7 115 1	Base Case	305.7	305.9	0.2
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	3	24LP0	659139 NESET__BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA.N_-MW7 115 655953 W.BANK_T-MW7 115 1	308.7	308.8	0.1
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	4	27LP0	659139 NESET__BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA.N_-MW7 115 655953 W.BANK_T-MW7 115 1	311.5	311.5	0
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.BEPM.LINDAHL	DPC	5	32LP0	659139 NESET__BE7 115 661085 TIOGA4 7 115 1	655952 TIOGA.N_-MW7 115 655953 W.BANK_T-MW7 115 1	328.3	328.5	0.2
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA. NEWHAMPTON	1	32SP0	659300 STANTN.T-BE7 115 659543 PICKCITY-RR7 115 1	P21:345:OTP:AUTO-SINGLE:CENTER3:COYOTE3:1	0	0	0
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA. NEWHAMPTON	2	32SP0	659543 PICKCITY-RR7 115 652442 GARRISN7 115 1	P21:345:OTP:AUTO-SINGLE:CENTER3:COYOTE3:1	0	0	0
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA.	3	24LP0	661008 BEULAH 7 115 661011 BEULAH27 115 Z	P21:345:OTP:AUTO-SINGLE:CENTER3:COYOTE3:1	5.8	5.9	0.1
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA.NE WHAMPTON	4	27LP0	661008 BEULAH 7 115 661011 BEULAH27 115 Z	P21:345:OTP:AUTO-SINGLE:CENTER3:COYOTE3:1	12.3	12.4	0.1
GEN-2017-048	156269	Jamestown 230 kV Capacitive Reactive Support (DISIS-2017-001)	WAUE.NWPS.COYOTE1	WAUE.NMCA.NE WHAMPTON	5	32LP0	661008 BEULAH 7 115 661011 BEULAH27 115 Z	P21:345:OTP:AUTO-SINGLE:CENTER3:COYOTE3:1	20.2	20.5	0.3

Southwest Power Pool, Inc.